

What It Includes:

	Therapy Unit with canister
	Dressing
	Carrying case with adjustable straps
	Three AA batteries
	Patch strips

What the Dressing Looks Like:

	The dressing should look wrinkled and the foam should be compressed.
	If the foam is not compressed or there is an alert on the therapy unit, see page 2 'Indicators and Alert' for what to do.



Watch the video (English)

How to Use the Therapy Unit

	Keep the unit turned on. You do not need to change the dressing. The unit will shut off on its own in 7 days. At that time, remove the dressing and throw the dressing and the therapy unit away in the trash.
	Keep the unit safe and dry. Do not drop it or let the tubing become bent, twisted or pinched. Keep the unit dry. See below for light showering.
	You may or may not see fluid collect in the canister. Some incisions drain more than others. Some don't drain at all. If the canister becomes completely full, turn off the unit and call Labor & Delivery # 617-414-2000
	Batteries It comes with three AA size batteries. If the batteries run out, see 'Therapy Unit Indicators and Alerts' on page 2 to replace the batteries.
	Sleeping with the Therapy Unit Put the dressing and pump in a place where the tubing will not bend, twist or pinch. Keep the therapy unit near your body so it doesn't fall off a table or bed onto the floor.
	Showering with the Therapy Unit Light showering is OK. Do not take a bath. • Keep the therapy unit away from direct water spray. [you can shut the unit off and disconnect the tubing if you like] • A little water or shower soap won't affect the dressing — it's okay to rinse lightly. • When towel drying, be careful not to disturb or damage the dressing.
	WARNING If the therapy unit falls into the tub, shower or sink, unplug the unit immediately (if plugged into an electrical source) and disconnect the unit from the dressing. Then contact Labor & Delivery # 617-414-2000

Therapy Unit Indicators and Alerts



Caution Indicator



Audible Alarm (muted)



Battery Level

Alert Type	How to Fix
Leak Alert One beep, one solid yellow light. 	To ensure proper application of the Therapy Unit - Double press ON/OFF button: One light = Best Two lights = Good Three lights = Marginal If "Marginal": 1. Make sure the canister is locked into the unit 2. Check the tubing connectors to make sure they are fully engaged and locked 3. Use a finger to smooth out any creases in the adhesive 4. Use Patch Strips (located in the dressing package) to help seal leaks 5. Slowly press firmly around dressing edges
Canister Full Alert Two beeps, one solid yellow light 	Check fluid level in the canister. 1. If the canister is not full check for kinks or pinched tubing 2. If the canister is full then turn the unit off 3. Call Labor & Delivery # 617-414-2000
Low Battery Alert Low One slow beep, one solid yellow light. Critical: One beep, repeating rapidly, increasing volume, two solid yellow lights 	This therapy unit comes with three AA batteries. To replace batteries: 1. Hold five second to turn off 2. Press and push the panel on the back of the unit to open 3. Insert three AA batteries (lithium batteries recommended) 4. Press and push to close panel 5. Hold two seconds to turn on
System Error Alert One beep, repeating rapidly, increasing in volume, two solid yellow lights 	1. Hold for five seconds to turn off 2. Hold two seconds to turn back on 3. If the therapy is still not running call Labor & Delivery # 617-414-2000
Device Lifecycle Expired Three lights show life cycle is up. There will be a repeated beep for 15 seconds and then the unit will shut off. 	Call Labor & Delivery # 617-414-2000 Life cycle = 192 hours (eight days)